

ControlLogix SERCOS interface Module, Firmware Revision 17

Catalog Numbers 1756-M03SE, 1756-M08SE, 1756-M16SE

When to Use These Release Notes

Use these release notes for firmware revision 17.16.

- ControlLogix 3 Axis SERCOS interface Module, 1756-M03SE
- ControlLogix 8 Axis SERCOS interface Module, 1756-M08SE
- ControlLogix 16 Axis SERCOS interface Module, 1756-M016SE

IMPORTANT

Before updating your ControlLogix SERCOS interface Module, we strongly recommend that you review information pertinent to previous major firmware revisions. For example, when updating from revision 16.x to 17.x, view information for revision 16 in the ControlLogix SERCOS interface Module, Revision 16 Release Notes, publication [1756-RN640](#), in addition to the content of these release notes.

Firmware release notes contain material for all minor revisions subsequent to each major revision. If your controller, for example, is at revision 16.3, and not the last minor revision, 16.5, you should view all of the information for revision 16.3...16.5 before updating to revision 17.16.

ControlLogix SERCOS interface Module, Revision 16 Release Notes, publication [1756-RN640](#), are available at <http://literature.rockwellautomation.com>.

Compatible Versions

To use firmware revision 17.16, update your system as follows.

Update	To Version
RSLinx Classic software	2.54 or later
RSLinx Enterprise software	5.17 or later
RSNetWorx software	9.00 or later
RSLogix 5000 software	17
ControlLogix controller	17.02

Corrected Anomaly in Firmware Revision 17.16

This firmware revision contains this corrected anomaly.

Corrected Anomaly	Description
All status indicators red.	Maintaining auxiliary power when power was cycled to drives could cause the SERCOS interface module to display solid red status indicators as power was cycled back to the drives.

Firmware Revision History

The following is a running history of release notes contained in ControlLogix SERCOS interface module, firmware revision 17.

Firmware Revision 17.15 Release Notes

Use these release notes for firmware revision 17.15.

IMPORTANT

Before updating your ControlLogix SERCOS interface Module, we strongly recommend that you review information pertinent to previous major firmware revisions. For example, when updating from revision 16.x to 17.x, view information for revision 16 in the ControlLogix SERCOS interface Module, Revision 16 Release Notes, publication [1756-RN640](#), in addition to the content of these release notes.

Firmware release notes contain material for all minor revisions subsequent to each major revision. If your controller, for example, is at revision 16.3, and not the last minor revision, 16.5, you should view all of the information for revision 16.3...16.5 before updating to revision 17.15.

ControlLogix SERCOS interface Module, Revision 16 Release Notes, publication [1756-RN640](#), are available at <http://literature.rockwellautomation.com>.

Compatible Versions

To use firmware revision 17.15, update your system as follows.

Update	To Version
RSLink Classic software	2.54 or later
RSLink Enterprise software	5.17 or later
RSNetWorx software	9.00 or later
RSLogix 5000 software	17
ControlLogix controller	17.02

Enhancement in Firmware Revision 17.15

This enhancement to the SERCOS motion module firmware lets you track significant events and errors from the SERCOS network ring. These events and errors can be retrieved into an array of 64 entries by using an RSLogix 5000 software message instruction.

You can diagnose and isolate log entries by programming a message instruction to clear the event/error log once phase 4 is established and/or the application is running.

For a full explanation of this feature, refer to the Knowledgebase ID 56209. To access Rockwell Automation's Knowledgebase, go to <http://www.rockwellautomation.com/knowledgebase>.

Firmware Revision 17.10 Release Notes

Use these release notes for firmware revision 17.10

IMPORTANT

Before updating your ControlLogix SERCOS interface Module, we strongly recommend that you review information pertinent to previous major firmware revisions. For example, when updating from revision 16.x to 17.x, view information for revision 16 in the ControlLogix SERCOS interface Module, Revision 16 Release Notes, publication [1756-RN640](#), in addition to the content of these release notes.

Firmware release notes contain material for all minor revisions subsequent to each major revision. If your controller, for example, is at revision 16.3, and not the last minor revision, 16.5, you should view all of the information for revision 16.3...16.5 before updating to revision 17.10.

ControlLogix SERCOS interface Module, Revision 16 Release Notes, publication [1756-RN640](#), are available at <http://literature.rockwellautomation.com>.

Compatible Versions

To use firmware revision 17.10, update your system as follows.

Update	To Version
RSLinx Classic software	2.54 or later
RSLinx Enterprise software	5.17 or later
RSNetWorx software	9.00 or later
RSLogix 5000 software	17
ControlLogix controller	17.02

Additional Resources

These documents contain additional information concerning related Rockwell Automation products.

Resource	Description
Industrial Automation Wiring and Grounding Guidelines, publication 1770-4.1	Provides general guidelines for installing a Rockwell Automation industrial system.
Product Certifications website, http://www.ab.com	Provides declarations of conformity, certificates, and other certification details.

You can view or download publications at <http://literature.rockwellautomation.com>. To order paper copies of technical documentation, contact your local Rockwell Automation distributor or sales representative.

Notes:

Notes:

Rockwell Automation Support

Rockwell Automation provides technical information on the Web to assist you in using its products. At <http://support.rockwellautomation.com>, you can find technical manuals, a knowledge base of FAQs, technical and application notes, sample code and links to software service packs, and a MySupport feature that you can customize to make the best use of these tools.

For an additional level of technical phone support for installation, configuration, and troubleshooting, we offer TechConnect support programs. For more information, contact your local distributor or Rockwell Automation representative, or visit <http://support.rockwellautomation.com>.

Installation Assistance

If you experience a problem within the first 24 hours of installation, please review the information that's contained in this manual. You can also contact a special Customer Support number for initial help in getting your product up and running.

United States	1.440.646.3434 Monday – Friday, 8 a.m. – 5 p.m. EST
Outside United States	Please contact your local Rockwell Automation representative for any technical support issues.

New Product Satisfaction Return

Rockwell Automation tests all of its products to ensure that they are fully operational when shipped from the manufacturing facility. However, if your product is not functioning and needs to be returned, follow these procedures.

United States	Contact your distributor. You must provide a Customer Support case number (call the phone number above to obtain one) to your distributor in order to complete the return process.
Outside United States	Please contact your local Rockwell Automation representative for the return procedure.

Allen-Bradley, Rockwell Automation, ControlLogix, RSLogix, RSNetWorx, RSLogix 5000, and TechConnect are trademarks of Rockwell Automation, Inc.

www.rockwellautomation.com

Power, Control and Information Solutions Headquarters

Americas: Rockwell Automation, 1201 South Second Street, Milwaukee, WI 53204-2496 USA, Tel: (1) 414.382.2000, Fax: (1) 414.382.4444
Europe/Middle East/Africa: Rockwell Automation, Vorstlaan/Boulevard du Souverain 36, 1170 Brussels, Belgium, Tel: (32) 2 663 0600, Fax: (32) 2 663 0640
Asia Pacific: Rockwell Automation, Level 14, Core F, Cyberport 3, 100 Cyberport Road, Hong Kong, Tel: (852) 2887 4788, Fax: (852) 2508 1846

Publication 1756-RN653C-EN-P - February 2009

PN-40752

Supersedes Publication 1756-RN653B-EN-P - November 2008

Copyright © 2009 Rockwell Automation, Inc. All rights reserved. Printed in the U.S.A.